

DTG Digital Color Learning Guide **Epson Printing - Photoshop CS5** on Windows

Epson Printing - Photoshop CS5 on Windows

Page: 1

The following instructions will guide you through the process of printing color images through Adobe Photoshop CS5 on a Windows operating system. Before we begin with the step by step guide, let's describe how to install ICC profiles as well as clarify DTG's nomenclature for our ICC profiles.

Install	ing ICC	C Profiles on a Windows System: -			Install Profile			
	1.	1. Download or copy the ICC profile to your desktop or other location on your computer.						
	2.	Right click the ICC profile and left cli That's it!	ick "Install Profile".		Cut Copy			
					Create Shortcut Delete Rename Properties			
Install	ing ICC	C Profiles on a Macintosh:	Applications Developer Addresug-Ins Applicauport	Calibrators	Black & White.icc Blue Tone.icc			
1. 2.	compu Copy t	oad or copy the ICC profile to your iter. he profile to the following folder: tosh HD/Library/Colorsync/Profiles	Caches Caches Caches Caches Caches Caches Caches Caches Caches Caches Caches Caches Colors Step byCS3.pdf System System Users Curmation Variant Components Users b. hosts Contex Items Lisers/s_b. hosts		 Displays DTG_apple cinema6500k22_120.ICC DTG_AppleCinema6500k22_120.icc DTG7-9880MK_F1WRCnv_USFA.icc DTG3800MK_HanGrmnEtch_EnMt.icc DTG3800MK_HanPiRag308_EnMt.icc DTG3800MK_HanPiRag308_EnMt.icc DTG3800MK_HanPiRag308_EnMt.icc 			

Interpreting DTG's Profile Names

Due to file name length limitations we must abbreviate many parts within the profile's name. We have tried to be very consistent in naming our profiles so look for this pattern: They always begin with the letters "DTG", followed by the printer model(s), followed by the black ink type (only if matte black is used), followed by the media name, finishing with the media setting you should set the driver to.

Example 1: DTG4880MK_HahnSmPhtRg308_USFA.icc

This is for an Epson **4880** printer using **M**atte Black ink, for **Hahn**emuhle **Sm**ooth **Photo Rag 308**gsm, and the media setting in the Epson driver should be set to **U**Itra **S**mooth **F**ine **A**rt Paper.

Example 2: DTG7898_Frd777Cnvs_Canvas.icc

This is for an Epson **78**00 or **98**00 printer using Photo Black ink (because there is no MK referenced in the name), for **Fr**edrix **777 Canvas**, and the media setting in the Epson driver should be set to **Canvas**.

Please Note: In some of our older profile names you may see the letters "ED". ED stands for Epson Driver and these letters are really unnecessary as all of our proifles are for the Epson driver unless we specify otherwise. **Also Note:** All of DTGs Epson ICC profiles are created for 1440x720 DPI printing resolution unless otherwise noted at the end of the profile name.


Please continue on to the following pages for a step by step process in printing color images from Adobe Photoshop CS5 on a Windows operating system.




DTG Digital Color Learning Guide *Epson Printing - Photoshop CS5 on Windows*

Epson Printing - Photoshop CS5 on Windows

Page: 2







DTG Digital Color Learning Guide **Epson Printing - Photoshop CS5** on Windows

Epson Printing - Photoshop CS5 on Windows


Page: 3

After you've selected Print, Photoshop's main print dialog box will pop up. Notice that your image may or may not fit within the default page size (usually letter size). In the example below, the image size is roughly 15.6 inches wide by 13.5 inches tall, so it's being "clipped" by the smaller 8.5x11 page size. Therefore, we need to select a larger page size

1.


If it's not the currently listed printer, click on the Printer drop list and select the Epson model you are printing to from the list of printers.

Click the Print Settings button so that we can select a proper page size. We will also set our driver specific settings for media, quality, and other options.





DTG Digital Color Learning Guide **Epson Printing - Photoshop CS5** on Windows



Main 🗊 Pa	age Layou	nt 🦉 l	Jtility											
S <u>e</u> lect Setting :	Current	Settings						•		Sav	e/ <u>D</u> el.			
Media Settings									22					
Media Type :	Canvas 💌									Custom Settings				
<u>Color</u> :	Color 🔹								Matte Black Ink					
Print Quality : Quality Options								•	Paper Config					
Mode :	O <u>A</u> uto	matic (O Cu	s <u>t</u> om										
4	Off (No Color Adjustment)							Adva <u>n</u> ced						
Paper Settings									52-12					
Source :	Roll Pap	er						•	Roll Paper Option					
Size :	Letter 8 1/2 x 11 in 🔹							User Defined						
	Borde	erless												
		Ink Lev	/els											
Print Pre <u>v</u> iew														
		C	0	Y	LC	MK	PK	VM	LK	G	LLK	VLM		
Reset Defaults	M						Ma	an <u>u</u> al			Versio	n 6.6		



Epson Printing - Photoshop CS5 on Windows

Digital Technology Group, Inc. www.DTGweb.com 800.681.0024 Tampa, FL DTG Digital Color Learning Guide *Epson Printing - Photoshop CS5 on Windows*

Page: 5

On this same Printer Properties window we can set our page size. You can select from a preset size list or create your own custom size. Our image in this example is an odd size - 15.6 inches wide by 13.5 inches tall so we will create a custom page size.

Click on the User Defined button next to the Size drop list in the Paper Settings Section.

* Please note that in choosing a paper size you do not need to select the size of the roll of paper that you have loaded in the printer. You just need to select or create a large enough page size that fits the image size of the file that you are trying to print.

elect Setting :	Current Settings									Save/Del				
Elect percently i										<u>save/p</u> erm				
Media Settings								_	_					
Media Type :	Canvas 👻							•	Custom Settings					
Color :						•	Matte Black Ink 👻							
Print Quality :	Quality Op	otions						•	Paper Config					
Mode :	Automatic Custom													
	Off (No Color Adjustment)							•	Adva <u>n</u> ced					
Paper Settings														
Source :	Roll Paper	ll Paper 🔹							Roll Paper Option					
Size :	Letter 8 1/2 x 11 in 🔹						•	User Defined			d			
	Borderless													
		Ink Lev	els											
Print Pre <u>v</u> iew														
		1000	100					188						
		С	0	Y	LC	MK	PK	VM	LK	G	LLK	VLM		
Reset Defaults	m					<u> </u>	Ma	anual	-		/ersio	n 6.62		



DTG Digital Color Learning Guide *Epson Printing - Photoshop CS5 on Windows*

Epson Printing - Photoshop CS5 on Windows

Page: 6

Once you click the User Defined button you will be brought to the following dialog where you can specify your own custom paper size.

Click inside the Paper Size Name box and change the name from "User Defined" to a name that corresponds to the size of the custom paper that you are creating. In this case we named it "17x15".



1.

Type in your desired paper width.

Type in your desired paper height.



5.

Click the Save Button.

Click OK

User Defined Paper Size	
Base Paper Size :	Paper Size Name :
User Defined 🔹	17x15
Paper Size : User Defined 17x15	Fix Aspect Ratio Not Specify Base: Carl Landscape Portrait
	Paper Width : 17.00
	Paper Height : 15.00 🚔 3
	(5.00 - 590.55) Unit () mm () inch
Save Delete	OK Cancel Help



DTG Digital Color Learning Guide **Epson Printing - Photoshop CS5 on Windows**

Epson Printing - Photoshop CS5 on Windows

Page: 7

Notice that the page size you just created is now showing in the Size: drop list. We are now finished with this properties box.



Main 🗊 Pa	age Layout	21	Itility											
S <u>e</u> lect Setting :	Current	Settings						•		Sav	e/ <u>D</u> el.)		
Media Settings								- 3-17	22					
Media Type : Canvas							Custom Settings							
<u>C</u> olor :	Color							•	▼ Matte Black Ink ▼					
Print Quality :	Quality Options 👻							Paper Config						
Mode :	<u>A</u> utomatic O Custom													
	Off (No Color Adjustment)								Adva <u>n</u> ced					
Paper Settings														
Source :	Roll Pape	Roll Paper 🔹								Roll Paper Option				
Size :	17x15 💌							User Defined						
	Borderless													
		Ink Lev	vels											
Print Pre <u>v</u> iew		I												
		C	0	Y	LC	MK	PK	VM	LK	G	LLK	VLM		
Reset Defaults	2						Ma	an <u>u</u> al)	/ersio	n 6.62		



DTG Digital Color Learning Guide *Epson Printing - Photoshop CS5 on Windows*

 Epson Printing - Photoshop CS5 on Windows
 Page: 8

 Once you exit the Printer Properties box you are back to Photoshop's Print dialog box. Notice that our image is not being clipped or cut off now that we've selected the proper page size. Now, we will set our color management specific settings in this dialog box.



3.

5.

Make sure you select "Color Management" from the drop list in the upper right. The choices are Output and Color Management.

- Choose "Photoshop Manages Colors" from the drop list under Color Handling.
- Choose the appropriate ICC profile from the printer profile drop list. This profile is specific to your printer, inkset, and the paper or media you are printing to. In the below example we will be printing to an Epson 7880 printer with matte black ink on Fredrix 777 Vivid Canvas.
- Choose a Rendering Intent: We recommend Perceptual or Relative Colorimetric. Either choice can subtly affect the output density or colors. Check Blackpoint Compensation.

We've now set all of the necessary settings - Click the Print Button.

17 ins x 15 ins	Printer: EPSON Stylus Pro 7900 🔻	Color Management (Document (Profile: Adobe RGB (1998))
	Copies: 1 Print Settings Position Center Image Top: 0.625 Left: 0.59 Scale do Pit Media Scale: 100% Height: 13.531 Width: 15.6 Print Resolution: 220 PPI Fint Resolution: 220 PPI	 Proof (Profile: N/A). Color Handling: Photoshop Manages Colors Printer Profile: DTG7-9900MK_Frd777Vvd_Can.icc Rendering Intent: Perceptual Ø Black Point Compensation Proof Setup: Working CMYK Simulate Paper Color Simulate Black Ink
Match Print Colors Gamut Warning Show Paper White	Units: inches 🔻	



DTG Digital Color Learning Guide **Epson Printing - Photoshop CS5 on Windows**

Epson Printing - Photoshop CS5 on Windows

Page: 9

We hope that this has been a helpful guide to you in your efforts in producing beautiful, color accurate prints on your Epson printer. If you have any further questions please do not hesitate to contact DTG at 800.681.0024. You can also visit our support page on our web site at http://www.dtgweb.com/support